

CAPRICORN-2 INSTALLATION MANUAL



IMPORTANT

READ CAREFULLY BEFORE INSTALLING FIXTURE. RETAIN THESE INSTRUCTIONS FOR FUTURE REFERENCE.

Fixtures must be wired in accordance with the National Electrical Code and all applicable local codes. Proper grounding is required for safety. THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.


WARNING: Make certain power is OFF before installing or maintaining fixture. No user serviceable parts inside

FIXTURE ASSEMBLY

1. Feed the (3) Housing wires through one of the three Rods.
2. Clip the (3) Rods onto the Housing. Be sure the Housing clips are properly engaged onto the Rods.
3. Feed Fixture Wires through the Tenon Pole Adaptor.
4. Slide Tenon Pole Adaptor on three Rods. Be sure the notches face the inside of the Tenon Pole Adaptor.
5. Tighten the (3) Set Screws at the Tenon Pole Adaptor to secure Rods

POLE MOUNTING

1. Make the wiring connections with UL approved connectors knot the wires for strain relief.
2. Slip Tenon Pole Adaptor over 2 3/8" diameter tenon and secure with the set screws on the side of Tenon Adaptor.




Note: These instructions do not cover all details or variations in equipment nor do they provide for every possible situation during installation operation or maintenance.

WIRING

Universal voltage driver permits operation at 100- 277VAC, 50/ 60Hz.

1. Connect the black fixture lead to the (+) LINE supply lead.
2. Connect the white fixture lead to the (-) COMMON supply lead.
3. Connect the bare copper Ground wire from fixture to supply ground.



CLEANING & MAINTENANCE

CAUTION: Be sure fixture temperature is cool enough to touch. Do not clean or maintain while fixture is energized.

1. Clean glass lens with non-abrasive glass cleaning solution.
2. Do not open fixture to clean the LED. Do not touch the LED.

TROUBLESHOOTING

1. Check that the line voltage at fixture is correct. Refer to wiring directions.
2. Is the fixture grounded properly?